

In the Claims:

1-10. (Canceled)

11. (Currently Amended) An s-mmwave imaging system, comprising

a non-rotating diffuser destroying a spatial coherence of radiation incident on the diffuser and directing the radiation towards a field of view, wherein the diffuser comprises a spatially distributed diffuser and wherein the diffuser comprises a plurality of spatially distributed point scatterers;

at least one radiation source disposed to illuminate the diffuser, the at least one radiation source generating radiation having a wavelength between about 0.1mm and about 10mm;

a quasi-optical element disposed between the field of view and a multi-element receiver, the quasi-optical element directing ~~directly~~ radiation from the field of view toward an imaging plane;

said multi-element receiver disposed in the imaging plane, wherein particular ones of the receiver elements transform radiation into a set of electrical signals; and

a processor coupled to receive the electrical signals from the receiver, the processor causing the point scatterers to be controlled based on information determined from the electrical signals.

12. (Previously Presented) The system of claim 100 wherein the diffuser comprises a spatially distributed diffuser.

13. (Original) The system of claim 12 wherein the diffuser comprises a plurality of spatially distributed point scatterers.

14. (Previously Presented) The system of claim 11 wherein the diffuser comprises a two-dimensional array of point scatterers, each of the point scatterers having a position and orientation which can be independently changed in time relative to a reference plane.

15. (Previously Presented) The system of claim 11 wherein the point scatterers comprise conductive structures being loaded by impedances.

16. (Original) The system of claim 13 and further comprising a processor coupled to receive the electrical signals from the receiver, the processor causing the point scatterers to be controlled based on information determined from the electrical signals.

17. (Original) The system of claim 11 and further comprising a processor coupled to receive the electrical signals from the receiver, the processor generating resultant images from the electrical signals.

18. (Original) The system of claim 11 wherein the radiation directed from the diffuser toward the field of view comprises a set of multiple phase-independent partials being independently controllable and exhibiting distinct physical features and wherein the electrical signals include information relating to features of the partials.

19. (Original) The system of claim 11 wherein the radiation incident on the diffuser includes doublet spectral components.

20-43 (Canceled)

44. (Previously Presented) A source of partially coherent radiation for illuminating a field of view, the source comprising:

at least one non-movable diffuser destroying a spatial coherence of radiation being incident on the diffuser and directing the radiation towards a field of view, the diffuser including an array of independently controllable radiation scatterers; and

at least one radiation emitting source being arranged to illuminate said diffuser with radiation;

wherein each radiation scatterer comprises a static high-Q resonant scatterer exhibiting frequency resonance belonging to a particular frequency band and wherein the radiation emitting source comprises a radiation source that sweeps over the particular frequency band.

45. (Original) The radiation source of claim 44 wherein each of the radiation scatterers is electronically controllable.

46. (Original) The radiation source claim 45 wherein each of the radiation scatterers is controllable by a time-varying modulation signal.

47. (Previously Presented) The radiation source of claim 46 wherein said radiation scatterers are assigned into sets and wherein each radiation scatterer within a set of radiation scatterers is modulated in the same manner.

48. (Original) The radiation source of claim 44 wherein the radiation scatterers can be independently controlled by physically moving the point scatterers with respect to a reference plane.

49. (Original) The radiation source of claim 44 wherein each radiation scatterer comprises a conductive structure loaded by an impedance.

50. (Canceled)

51. (Original) The radiation source of claim 44 wherein the at least one radiation emitting source is arranged to illuminate the diffuser with radiation having a wavelength between about 0.1mm to about 10mm.

52. (Original) A millimeter wave system comprising:
a source of radiation, the radiation comprising a set of independently controllable radiation components, each radiation component comprising a doublet that includes two spectral lines, and each radiation component being labeled by a given frequency shift between the two spectral lines;

a receiver including an array of receiver elements disposed to receive the radiation emitted by the source, the receiver transforming the received radiation into an array of electrical signals; and

a processing system coupled to receive the array of electrical signals and for decoding the array of electrical signals based on the labels of the radiation components.

53. (Original) The system of claim 52 wherein the processing system is coupled to the source of radiation to provide instructions on how to control the radiation components.

54. (Original) The system of claim 52 wherein the frequency difference between the two spectral lines is modulated.

55. (Original) The system of claim 52 wherein the central frequency of the two spectral lines is swept in time.

56. (Original) The system of claim 52 wherein the two spectral lines comprise a co-polarized doublet and wherein the source of radiation comprises:

a pair of voltage controlled oscillators operating at a s-mmwave frequency and having a first characteristic polarization state;

a set of load-modulated point scatterers that are illuminated by the voltage controlled oscillators, the set of load-modulated point scatterers being preferentially sensitive to the first characteristic polarization state;

wherein the load of each point scatterer is modulated with a time varying signal; and

wherein the scattered radiation is directed to an object being imaged.

57. (Original) The system of claim 52 wherein the source of radiation is in a substrate configuration, the source further comprising means to combine the radiation of the two spectral lines of each component.

58. (Original) The system of claim 52 wherein the source of radiation is in a waveguide configuration, the source further comprising means to combine the radiation of the two spectral lines of each component.

59. (Previously Presented) A method for creating radiation that includes a polarized doublet, the method including:

emitting radiation at a first s-mmwave frequency;

emitting radiation at a second s-mmwave frequency, wherein the difference between the first s-mmwave frequency and the second s-mmwave frequency is much smaller than the average of the first s-mmwave frequency and the second s-mmwave frequency;

controlling the difference between the first s-mmwave frequency and the second s-mmwave frequency;

polarizing the radiation at the first s-mmwave frequency into a first characteristic polarization;

polarizing the radiation at the s-mmwave frequency into a second characteristic polarization;

combining the radiation at the first s-mmwave frequency and the radiation at the second s-mmwave frequency; and

directing the combined radiation to a destination.

60. (Original) The method of claim 59 wherein the first polarization is essentially equal to the second polarization.

61. (Original) The method of claim 59 wherein the first polarization is essentially orthogonal to the second polarization.

62. (Canceled).

63. (Currently Amended) The method of claim 59 ~~claim 62~~ wherein the combined radiation is divided into two unequal parts, a major part being directed to the destination and a minor part being used to control the difference frequency.

64. (Original) The method of claim 59 and further comprising changing average of the first s-mmwave frequency and the second s-mmwave frequency.

65. (Original) The method of claim 59 and further comprising modulating the difference between the first s-mmwave frequency and the second s-mmwave frequency.

66. (Original) The method of claim 59 wherein the method is performed in a waveguide configuration.

67. (Original) The method of claim 59 wherein the method is performed in a planar substrate configuration.

68. (Original) A method of creating radiation that includes a cross-polarized doublet, the method comprising:

providing a voltage controlled oscillator operating at a first s-mmwave frequency;

directing energy of the oscillator to uniformly illuminate first and second sets of load-modulated point scatterers, the first set exhibiting a first polarization state and the second set exhibiting a second polarization state, wherein the first polarization state is orthogonal to the second polarization state;

polarizing the oscillator in a third characteristic polarization state;

positioning the first and second sets of point scatterers such that the first and second polarization state substantially differs from the third characteristic polarization state;

modulating the load of the first scatterer with a first time varying signal;

modulating the load of the second scatterer with a second time varying signal, wherein the ground harmonic of first time varying signal essentially differs from any harmonic of the second harmonic time varying signal; and

scattering radiation from the first and second sets of point scatterers.

69. (Original) The method of claim 68 wherein the first and second time varying signals are periodic signals.

70. (Original) The method of claim 69 wherein the sum of the ground harmonics of the first periodic signal and the second periodic signal is equal to a doublet frequency difference.

71. (Original) The method of claim 69 wherein the difference of the ground harmonics of the first periodic signal and the second periodic signal is equal to a doublet frequency difference.

72. (Original) The method of claim 69 wherein the periodic signals are binary signals.

73. (Original) The method of claim 69 wherein the periodic signals are harmonic signals.

74. (Original) The method of claim 69 and further comprising controlling the difference frequency between the periodic signals by dividing the energy of both periodic signals in unequal parts, a major part being used to drive first and second loads and the minor part being used to control the difference frequency.

75-82 (Canceled)

83. (Original) A millimeter wave transmitter-receiver apparatus for transmitting and receiving image or communication data comprising:

a source of radiation, the radiation comprising a set of independently controllable radiation components, each radiation component comprising a doublet that includes two spectral lines, and each radiation component being labeled by a given frequency shift between the two spectral lines;

a receiver including an array of receiver elements disposed to receive the radiation emitted by the source, the receiver transforming the received radiation into an array of electrical signals; and

a processing system coupled to receive the array of electrical signals and for decoding the array of electrical signals based on the labels of the radiation components.

84. (Currently Amended) The apparatus system of claim 83 wherein the processing system is coupled to the source of radiation to provide instructions on how to control the radiation components.

85. (Currently Amended) The apparatus system of claim 83 wherein the frequency difference between the two spectral lines is modulated.

86. (Currently Amended) The apparatus system of claim 83 wherein the central frequency of the two spectral lines is swept in time.

87. (Currently Amended) The apparatus system of claim 83 wherein the two spectral lines comprise a doublet and wherein the source of radiation comprises:

at least one pair of voltage controlled oscillators operating at different s-mmwave frequencies;

a plurality of paired couplers each of which is individually coupled to an output of one of the voltage-controlled oscillators (VCOs) for dividing VCO radiation into a major portion for transmitting in free space and a minor portion for mixing;

a first mixer for mixing the minor radiation portion the VCO radiation to produce a first beat signal;

a phase locked loop (PLL) circuit providing phase-locking of the first beat signal by the reference signal, wherein one input of the PLL circuit is supplied by the first beat signal, another PLL circuit input is supplied by the reference signal and an output correction voltage produced by the PLL circuits is provided to a frequency correcting driving voltage input of one of the VCOs; and

an antenna system to transmit the major radiation portions produced by the VCOs in free space.

88. (Previously Presented) The system of claim 11 wherein the spatially distributed point scatterers are disposed on a corrugated substrate.

89. (Previously Presented) The system of claim 11 wherein each of the point scatterers change the phase of scattered radiation independently of others of the point scatterers.

90. (Previously Presented) The system of claim 11 wherein each of the point scatterers change the frequency distribution of scattered radiation independently of others of the point scatterers.

91. (Previously Presented) The system of claim 15 wherein magnitudes of the impedances of the loaded structures are time-varied due to modulation.

92. (Currently Amended) The system of claim 91 wherein said spatially distinct scatterers are modulated by signals exhibiting distinct modulation features.

93. (Previously Presented) The system of claim 92 wherein one of the distinct modulation features is the frequency of the modulation signals.

94. (Currently Amended) The system of claim 91 wherein the point scatterers are divided into sets and wherein each point scatterer within a set of point scatters is modulated ~~with~~ by the same modulation signal.

95-96 (Canceled)

97. (Currently Amended) The system of claim 94 wherein each set of point scatterers is frequency modulated by a unique modulating signal, wherein the frequencies of the modulation signals are distinct ~~and narrowly ranging~~.

98. (Currently Amended) The system of claim 94 wherein the composition of each set of point scatterers can be dynamically changed.

99. (Previously Presented) The system of claim 15 wherein the conductive structures comprise antennae.

100. (Currently Amended) An s-mmwave imaging system, comprising:

a non-rotating diffuser destroying a spatial coherence of radiation incident on the diffuser and directing the radiation towards a field of view, wherein the radiation incident on the diffuser includes doublet spectral components and wherein the radiation incident on the diffuser is modulated by modulating a spectral shift between doublet spectral components;

at least one radiation source disposed to illuminate the diffuser, the at least one radiation source generating radiation having a wavelength between about 0.1mm and about 10mm;

a quasi-optical element disposed between the field of view and a multi-element receiver, the quasi-optical element directing ~~directly~~ radiation from the field of view toward an imaging plane; and

[[a]] said multi-element receiver disposed in the imaging plane, wherein particular ones of the receiver elements transform radiation into a set of electrical signals.

101. (Previously Presented) The system of claim 13 wherein the diffuser comprises a two-dimensional array of point scatterers, each of the point scatterers having a position and orientation which can be independently changed in time relative to a reference plane.

102. (Previously Presented) The system of claim 13 wherein the point scatterers comprise conductive structures being loaded by impedances.

103. (Previously Presented) The system of claim 100 and further comprising a processor coupled to receive the electrical signals from the receiver, the processor generating resultant images from the electrical signals.

104. (Currently Amended) The system of claim 100 wherein the radiation directed from the diffuser toward the field of view comprises a set of multiple phase-independent partials being independently controllable and exhibiting distinct physical features and wherein the electrical signals include information relating to said features of the partials.

105. (Previously Presented) The radiation source of claim 44 wherein the radiation scatterers are disposed on a corrugated substrate.

106. (Previously Presented) The radiation source of claim 44 wherein the radiation scatterers have polarization selective characteristics.

107. (Currently Amended) The radiation source of claim 44 wherein the radiation point scatterers have frequency selective characteristics.

108. (Previously Presented) The radiation source of claim 46 wherein the modulation signal exhibits distinct modulation features for distinct scatterers.

109. (Previously Presented) The radiation source of claim 46 wherein the radiation scatterers are controlled by frequency-modulated modulation signals.

110. (Canceled)

111. (Previously Presented) The radiation source of claim 47 wherein the sets are assigned according to an angle of incidence of radiation scattered by the diffuser.

112. (Previously Presented) The radiation source of claim 111 wherein the sets are dynamically assigned.

113. (Previously Presented) The radiation source of claim 48 wherein each radiation scatterer is under piezoelectric control.

114. (Previously Presented) The radiation source of claim 48 wherein each radiation scatterer is under electromagnetic control.

115. (Previously Presented) The radiation source of claim 44 wherein each radiation scatterer is controlled by an electric signal.

116. (Previously Presented) The radiation source of claim 44 wherein each radiation scatterer is controlled by an optical signal.

117. (Canceled)

118. (Previously Presented) The radiation source of claim 49 wherein each radiation scatterer includes a resistive element.

119. (Previously Presented) The radiation source of claim 49 wherein each radiation scatterer includes an inductive element.

120. (Previously Presented) The radiation source of claim 49 wherein each radiation scatterer includes a capacitive element.

121. (Canceled)

122. (Currently Amended) The radiation source of claim 44 ~~claim 50~~ wherein the radiation scatterers comprise antennas with closely spaced frequency resonances that are spatially clustered in given geometrical profiles.

123. (Previously Presented) The system of claim 52 wherein the two spectral lines have co-polarization characteristics.

124. (Previously Presented) The system of claim 52 wherein the two spectral lines have cross-polarization characteristics.

125. (Previously Presented) The system of claim 52 wherein the receiver elements comprise mixers which generate difference frequency signals for the radiation components.

126. (Currently Amended) The system of claim 52 wherein the source of radiation includes:
a first voltage controlled oscillator operating at a first frequency;

a second voltage controlled oscillator operating at a second frequency; and

an embedded mixer;

wherein the combined energy of the first and second voltage controlled oscillators is divided into two unequal parts, a major part being used to direct ~~to a to the~~ destination and a minor part being used to control a difference frequency between the two spectral lines by mixing the minor part in the embedded mixer.

127. (Currently Amended) The system of claim 52 wherein the two spectral lines comprise a cross-polarized doublet and wherein the source of radiation includes:

a first set of load-modulated point scatterers, the first set exhibiting a first ~~second~~ polarization state;

a second set of load-modulated point scatterers, the second set exhibiting a second polarization state, the first polarization state being orthogonal to the second polarization state; and

a voltage controlled oscillator operating at an s-mmwave frequency having a third characteristic polarization state which differs from the said first and second ~~characteristic~~ polarization states, the voltage controlled oscillator illuminating the first and second sets of load-modulated point scatterers.

128. (Previously Presented) The system of claim 56 wherein the time varying signal is a periodic signal.

129. (Canceled)